

# INSTALLATION INSTRUCTIONS

FOR ITEM 195179 NIDOS 4 LT PENDANT

*Meyda*  
CUSTOM LIGHTING

**CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE.** We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.\*

**Caution:** Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

## FIXTURE COMPONENTS

- A. 42"W CEILING PLATE
- B. 12"W MESH GLOBE W/ SOCKET & 72"WIRE
- C. 16"W MESH GLOBE W/ SOCKET & 72"WIRE
- D. 18"W MESH GLOBE W/ SOCKET & 72"WIRE
- E. 20"W MESH GLOBE W/ SOCKET & 72"WIRE
- F. ANCHOR BOLT W/ HEX & ACORN NUT (QTY 8)
- G. CABLE CRIMP (QTY 4)

**Caution: Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.**

1. Carefully unpack all components and make certain that everything is accounted for.
2. Unscrew Tapered Coupler on top of Mesh Globe and slide Coupler and Globe Cap up Wire.
3. Allow Socket and Shade Bracket to lower into Globe, tilt slightly and withdraw from Globe.
4. Install Medium Base 15Watt LED Bulb(not included) into Socket.
5. Tilting at slight angle, insert Socket with Bulb and Shade Bracket into Globe.
6. Hold Socket to allow Shade Bracket to rest under lip of Globe opening. Slide Globe Cap and Coupler down Wire and Screw Coupler onto Threaded Nipple until tight.
7. Feed loose end of Wire through Tapered Coupler in Ceiling Plate.
8. Set desired Drop of Globe by closing Cable Crimp around wire on top of Ceiling Plate.
9. Repeat steps 2-8 for 3 remaining Globes.
10. Make electrical connection from Globe Lead Wires to Structure Supply Wires following all Local Codes and Procedures.
11. Move Fixture into position and attach to structure using provided Anchor Bolts w/ Hex & Acorn Nuts.
12. Power on and Enjoy!!!

