

INSTALLATION INSTRUCTIONS

FOR ITEM 210611 LANDSHARK 3 LIGHT CHANDELIER

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

- | | |
|--|---------------------------------|
| 1. MOUNTING PLATE w/STEM BOLT (QTY 3) | 5. SURBOARD CONNECTION HARDWARE |
| 2. LEAD WIRE STEM (2 PLUGS AT PLATE END) | 6. BEER BOTTLES (QTY 39) |
| 3. OUTER STEM (QTY 2) | |
| 4. SURFBOARD w/BUCKET SHADES | |

Caution:

Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box. Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.

1. Carefully unpack all components and make certain that everything is accounted for.
2. Using Customer Supplied Bolts, secure Mounting Plates to ceiling ensuring that cumulative connections will hold a minimum of 100lbs.
3. Remove Stem Bolts from Mounting Plates and reserve.
4. Remove Screws from each Wireway Cover and remove Covers. Reserve Screws for later use.
5. Locate Lead Wire Stem and make Wire connection from Plug at bottom to center Plug on Surfboard.
6. Using provided Surfboard Connection Hardware, attach Stem to Surfboard.
7. Make Wire connections from Plugs at bottom of Outer Stems to Plugs at either end of Surfboard.
8. Using provided Surfboard Connection Hardware, attach Stems to Surfboard. Ensure that loose ends of Wires exiting side of Stems are facing center of Board.
9. Run Wires from Outer Stems to center of Board and make Wire connections at Lead Wire Stem.
10. Replace Wireway Covers ensuring not to pinch Wires and secure with reserved Screws.
11. Following all Local Codes and Procedures, make electrical connection from Lead Wires to Supply Wires.
12. Hang fixture by inserting Stems into Mounting Plates and securing with reserved Stem Bolts.
13. Remove Hex Nuts and Bottle Frames from insides of Bucket Shades.
14. Install 3-E26 60Watt PAR30 Bulbs(not included) into Sockets.
15. Replace Bottle Frames and secure with Hex Nuts.
16. Connect Bottle Clips from Bottles to Frames inside Bucket Shades. 13 Bottles per Bucket.
17. Power on and ENJOY!!!

INSTALLATION INSTRUCTIONS

FOR ITEM 210611 LANDSHARK 3 LIGHT CHANDELIER

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

1. MOUNTING PLATE w/STEM BOLT (QTY 3)
2. LEAD WIRE STEM (2 PLUGS AT PLATE END)
3. OUTER STEM (QTY 2)
4. SURFBOARD w/BUCKET SHADES
5. SURFBOARD CONNECTION HARDWARE
6. BEER BOTTLES (QTY 39)

Caution:

Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box.
Be sure power is off at the main breaker box prior to installation.
Read all instructions in their entirety before beginning installation.

