

# INSTALLATION INSTRUCTIONS

FOR ITEM 231107 CEILING MEDALLION

*Meyda*  
CUSTOM LIGHTING

**CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE.** We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.\*

**Caution:** Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

## **Caution:**

**Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box. Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.**

1. Carefully unpack all components and make certain that everything is accounted for.
2. Remove Acorn Nuts from Ceiling Medallion to release Mounting Plate. Reserve Acorn Nuts for later use.
3. Using Customer Supplied Hardware, affix Mounting Plate to ceiling ensuring that connection is suitable to hold a minimum of 80lbs for Medallion plus weight of Customer Chandelier.
4. Fixture is wired with Two Circuits to allow for separate levels of light to be controlled independently of one another if desired. Lead Wires are labeled, one for Upper Ambient Light and one for Task Down Lights. Following all Local Codes and Procedures, make electrical connection from Ceiling Medallion Lead Wires to Supply Wires. If dimming is desired, connect Fixture Wires to Triac/ELV Dimmer Wires.
5. Once successful wiring connections have been made, lift Medallion up to ceiling allowing Mounting Plate Studs to protrude through. Secure Fixture with reserved Acorn Nuts.
6. Hang Customer Chandelier from Loop at center of Medallion.
7. Power on and ENJOY!!!

