

# INSTALLATION INSTRUCTIONS

FOR ITEM 141870 SMYTHE CRAFTSMAN CHANDEL-AIR

*Meyda*  
CUSTOM LIGHTING

**CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE.** We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.\*

**Caution:** Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

## FIXTURE COMPONENTS

1. CANOPY ASSEMBLY
2. DOWN ROD
3. CHANDEL-AIR BODY

### Caution:

**Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box.**  
**Be sure power is off at the main breaker box prior to installation.**  
**Read all instructions in their entirety before beginning installation.**

1. Carefully unpack all components and make certain that everything is accounted for.
2. Using Customer Supplied Hardware, affix Mounting Saddle to blocking in ceiling ensuring that connection is suitable to hold minimum of 100lbs and that Electrical Supply Wires remain accessible.
3. Unravel Fixture Lead Wires from top of Chandel-Air Body and feed through Down Rod.
4. Attach Down Rod Plate to top of Chandel-Air Body and secure with Hex and Acorn Nuts.
5. Feed Lead Wires through Canopy Cover Plate and Canopy and carefully slide them down Rod and allow them to rest on top of Chandel-Air Body.
6. Feed Lead Wires through Steel Half Ball and slide Half Ball onto Down Rod.
7. Feed Spring Pin through holes at top of Down Rod.
8. Slide Half Ball up Rod and allow Spring Pin to snap into Half Ball Channel.
9. Lift Fixture up to ceiling and seat Steel Half Ball into Mounting Saddle.
10. Following all Local Codes and Procedures, make electrical connections from Fixture Lead Wires to Supply Wires.
11. Carefully slide Canopy and Cover Plate up Rod and secure to Mounting Saddle Studs using Brass Balls.
12. Install 8-E26 60Watt Bulbs(not included) into Sockets.
13. Power on and ENJOY!!!

