

INSTALLATION INSTRUCTIONS

FOR ITEM 193772 JAYNE 2 TIER PENDANT

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

- A. 48"W PENDANT BODY
- B. 85.25" THREADED ROD INSIDE 84" CONDUIT
- C. CANOPY ASSEMBLY

Caution: Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.

1. Carefully unpack all components and make certain that everything is accounted for.
2. Remove Acorn and Hex Nuts from Canopy Assembly to release Mounting Plate. Reserve all Nuts for later use.
3. Affix Mounting Plate to ceiling ensuring that connection is suitable for minimum 75lbs and that Electrical Supply Wires remain accessible.

If desired, overall height of Fixture can be reduced by cutting equal length from Threaded Rod and Conduit before continuing. Threaded Rod should be 1.25" longer than Conduit after cuts.
4. Unravel Fixture Lead Wires from top of Pendant Body and feed through Threaded Rod. Wire should enter end of rod without Hex Nut.
5. Screw Threaded Rod into Coupler at top of Pendant Body.
6. Remove Hex Nut and Spider Washer from loose end of Threaded Rod.
7. Feed Lead Wires and Threaded Rod through Canopy and fasten with Spider Washer and Hex Nut.
8. Make electrical connection from Fixture Lead Wires to Supply Wires following all Local Codes and Procedures.
9. Install 6 Medium Base 60Watt Bulbs(not included) into Sockets.
10. Lift Fixture into position sliding Canopy over Mounting Plate Studs and secured with Hex and Acorn Nuts.

11. Power on and ENJOY!!!

