

INSTALLATION INSTRUCTIONS

FOR ITEM 210476 CILINDRO CAMPBELL PENDANT

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

1. CANOPY ASSEMBLY
2. SQUARE CHAIN (144")
3. PENDANT BODY

Caution:

Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box. Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.

1. Carefully unpack all components and make certain that everything is accounted for.
2. Unscrew Collar to release Mounting Plate with Brass Loop and Quick Link.
3. Affix Mounting Plate to ceiling ensuring that connection is suitable to hold a minimum of 75lbs and that Electrical Supply Wires remain accessible.
4. Unravel Fixture Lead Wires and Safety Cable from top of Pendant Body and attach Square Chain to Quick Link.
5. Weave Fixture Lead Wires and Safety Cable through every 3rd Link of Chain.
6. Feed Fixture Lead Wires and Safety Cable through Screw Collar and Canopy and allow them to rest on top of Chain.
7. Lift Fixture into position and hang by connecting loose end of Chain to Quick Link on Brass Loop.
8. Feed Safety Cable through Channel in Brass Loop and secure to structure ensuring that the connection is suitable to hold a minimum of 75lbs.
9. Feed Fixture Lead Wires through Channel in Brass Loop and, following all Local Codes and Procedures, make electrical connection from Lead Wires to Structure Supply Wires.
10. Lift Canopy up to ceiling and screw Collar onto Brass Loop until top of Canopy is flush with ceiling.
11. Install 12 Medium Base 40Watt T10 Bulbs(not included) into Sockets.
12. Power on and ENJOY!!!

