

# INSTALLATION INSTRUCTIONS

FOR ITEM 215766 (7" Wide Miners Lantern Wall Sconce)

*Meyda*  
CUSTOM LIGHTING

**CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE.** We recommend installation by a licensed electrician.

This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.\*

**Caution:** Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

## FIXTURE COMPONENTS

1. BACKPLATE ASSEMBLY (BACKPLATE, CROSSBAR W/ STUDS)
2. LANTERN
3. CANDLE COVER

### **Caution:**

***Be sure power is off at the main breaker box prior to installation.***

***Read all instructions in their entirety before beginning installation.***

1. Carefully unpack all components and make certain that everything is on hand.
2. Unscrew the Brass Balls from Backplate Assembly to release the Crossbar.
3. Using customer supplied hardware, affix the Crossbar directly to the J-Box, ensuring the connection is suitable for a minimum of 15 lbs. and that electrical supply wires remain accessible.
4. Following all local codes and procedures, make electrical wire connections from supply wire to fixture lead wires.
5. Resecure the Lantern with Backplate to the Crossbar with Brass Balls.
6. Slide the top up and slide the Glass out of the Lantern.
7. Install the Candle Cover over socket.
8. Install 60W E12 BA9 Bulbs (not included) into sockets.
9. Reinstall the Glass by sliding the top up.
10. Power On and ENJOY!!!

