

INSTALLATION INSTRUCTIONS

FOR ITEM 218561 OAK LEAF 15 LIGHT CHANDELIER

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

1. CANOPY ASSEMBLY
2. 180" CHAIN
3. CHANDELIER BODY
4. CANDLE COVERS (QTY 15)

Caution:

Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box. Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.

1. Carefully unpack all components and make certain that everything is accounted for.
2. Unscrew Collar from Canopy Assembly to release Crossbar with attached Loop.
3. Using Customer Provided Hardware attach Crossbar to Reinforced J-Box ensuring connection is suitable to hold a minimum of 50lbs and that Electrical Supply Wires remain accessible.
4. Attach desired length of Chain to Quick Link at top of Chandelier Body.
5. Weave Fixture Lead Wires and Safety Cable through every 5th Link of Chain.
6. Slide Screw Collar and Canopy over Wires, Cable, and Chain and allow them to rest on top of Chandelier Body.
7. Lift Chandelier Body and hang by attaching loose end of Chain to Quick Link on Crossbar Loop.
8. Feed Safety Cable through channel in Crossbar Loop and secure to structure ensuring that connection is suitable to hold a minimum of 50lbs.
9. Feed Fixture Lead Wires through Crossbar Loop and, following all Local Codes and Procedures, make electrical connection to Electrical Supply Wires.
10. Slide Canopy up Chain to ceiling and secure by screwing Collar onto Crossbar Loop.
11. Chandelier Arms should be rotated until they are evenly spaced apart from each other. If desired, leaves can also be adjusted by gently bending them into position.
12. Place Candle Covers over Sockets.
13. Install 15 Candelabra Base 60Watt Bulbs(not included) into Sockets.
14. Power on and ENJOY!!!

