

# INSTALLATION INSTRUCTIONS

FOR ITEM 223475 KITZI TAPERED PENDANT

*Meyda*  
CUSTOM LIGHTING

**CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE.** We recommend installation by a licensed electrician. This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.\*

**Caution:** Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

## FIXTURE COMPONENTS

1. CANOPY ASSEMBLY
2. 96" CHAIN
3. PENDANT BODY
4. CANDLE COVER (QTY 8)

### **Caution:**

**Fixture is OVERWEIGHT and not suitable for installation with standard Junction Box. Be sure power is off at the main breaker box prior to installation. Read all instructions in their entirety before beginning installation.**

1. Carefully unpack all components and make certain that everything is accounted for.
2. Unscrew Collar from Canopy Assembly to release Crossbar with attached Loop.
3. Affix Crossbar to ceiling ensuring that connection is suitable to hold a minimum of 50lbs and that Electrical Supply Wires remain accessible.
4. Attach desired length of Chain to Quick Link at top of Pendant Body.
5. Weave Fixture Lead Wires and Safety Cable through every 3rd Link of Chain.
6. Slide Screw Collar and Canopy over Chain, Wires, and Cable and allow them to rest on top of Pendant Body.
7. Hang Fixture by attaching loose end of Chain to Quick Link on Crossbar Loop.
8. Feed Safety Cable through Channel in Crossbar Loop and attach to secure location. Ensure that connection is suitable to hold a minimum of 50lbs.
9. Feed Fixture Lead Wires through Channel in Crossbar Loop and, Following all Local Codes and Procedures, make electrical connection from Lead Wires to Supply Wires.
10. Slide Canopy up Chain to ceiling and secure by screwing Collar onto Crossbar Loop.
11. Place Candle Covers over Sockets.
12. Install 8 Candelabra Base 60Watt Bulbs(not included) into Sockets.
13. Power on and ENJOY!!!

