

INSTALLATION INSTRUCTIONS

FOR ITEM 285453 (18" SQUARE BALSAM PINE INVERTED PENDANT)

Meyda
CUSTOM LIGHTING

CAUTION: FAILURE TO INSTALL THIS FIXTURE PROPERLY MAY RESULT IN SERIOUS PERSONAL INJURY OR DEATH AND PROPERTY DAMAGE. We recommend installation by a licensed electrician.

This product must be installed in accordance with applicable installation code(s), by a person familiar with the construction and operation of the product and the hazards involved.*

Caution: Do not exceed maximum wattage noted on fixture. Use only recommended bulbs with fixture.

FIXTURE COMPONENTS

1. CANOPY ASSEMBLY
2. FIXTURE FRAME
3. HUB ASSEMBLY

Caution:

***Be sure power is off at the main breaker box prior to installation.
Read all instructions in their entirety before beginning installation.***

1. Carefully unpack all components and make certain that everything is on hand.
2. Unscrew Collar on end of Loop attached to Canopy to release the Canopy from Crossbar.
3. Using customer supplied hardware, affix crossbar directly to J-box ensuring that connection is suitable for a minimum of 30 lbs and that electrical supply wires remain accessible.
4. Unravel the lead wires from top of the Hub and attach desired length of Chain to Quick Link.
5. Weave fixture lead wires through Chain.
6. Slide Screw Collar and Canopy over wire and Chain and allow them to rest on top of Hub.
7. Hang Hub by attaching loose end of Chain to Quick Link on Crossbar Loop.
8. Following all local codes and procedures, make electrical connection from supply wires to fixture lead wires.
9. Lift Canopy up Chain to ceiling and tighten in place using Screw Collar.
10. Install 4 X 60 WATT Max E26 A19 Bulbs (not included) into socket.
11. Hung Shade on Hub using Arms
12. Power on and ENJOY!!!

